

Brushless Motoren

EFLM1000



EFLM1100



EFLM1120



EFLM1130



EFLM1150



EFLM1200



EFLM1205




EFLM1300



EFLM1305



EFLM1340DF



EFLM1400



EFLM1500



EFLM1600




Nummer	Bezeichnung	Länge mm	Ø mm	Welle mm	Zellenzahl	LiPo	Leerlaufstrom	Innenwiderstand	Dauerstrom	Drehzahl Volt	Gewicht gr.	Propeller	Modellgewicht gr.
EFLM1000*	Park 370	30	20	2	6-10	2-3	1A	0,10 Ohm	8A	4.100	48	9x6-12x6	280-400
EFLM1100*	Park 400	40	20	2	6-10	2-3	1,8A	0,24 Ohm	18A	4.200	68	10x4,7-12x6	340-740
EFLM1120	Park180	20	16	1,5	6-10	2-3	0,3A	0,91 Ohm	2,6A	2.200	8,5	3x3-6x3	85-170
EFLM1130	Outrunner Park 250	23	22	3,17	6-8	2	0,45A	0,25 Ohm	7A	2.200	14	5.5x4.5-8x6	115-170
EFLM1150	Outrunner Park 300	22	28	3,17	6-8	2	0,4A	0,33 Ohm	7A	1380	24	6x5-8x3,8	170-255
EFLM1200	Outrunner Park 370	25	28	3,17	6-10	2-3	0,7A	0,19 Ohm	7A	1.080	45	9x4,7-10x4,7	200-400
EFLM1205	Outrunner Park 370	25	28	3,17	6-8	2	1A	0,10 Ohm	9A	1.360	45	8x6-9x4,7	200-400
EFLM1300	Outrunner Park 400	29	28	3,17	6-10	2-3	0,54A	0,26 Ohm	7A	740	56	10x7-12x3,8	280-560
EFLM1305	Outrunner Park 400	29	28	3,17	6-10	2-3	0,7A	0,10 Ohm	10A	920	56	9x7-11x4,7	280-560
EFLM1340DF	Outrunner BL420 D.Fan	30	28	2.3	8-10	3S	1,8A	0,03 Ohm	25A	3800	58	Fan Unit 66mm	450-800
EFLM1400	Outrunner Park 450	33	28	4	6-10	2-3	0,69A	0,20 Ohm	14A	890	72	9x6-11x3,8	420-700
EFLM1500	Outrunner Park 480	33	35	4	6-10	2-3	0,85A	0,08 Ohm	20A	910	87	10x7-12x6	710-990
EFLM1505	Outrunner Park 480	33	35	4	6-10	2-3	1,10A	0,06 Ohm	22A	1020	87	10x7-12x6	710-990

Die mit * gekennzeichneten Motoren sind Innenläufer und die Laufschaubengrösse beziehen sich auf den Bereich mit einem Getriebe

Änderungen vorbehalten! - Sous réserve de toutes modifications!

Brushless Motoren

EFLM4010A



EFLM4015A



EFLM4025A



EFLM4032A



EFLM4046A



EFLM4060A



EFLM4110A



EFLM4160A



Nummer	Bezeichnung	Länge mm	Ø mm	Welle mm	Zellenzahl	LiPo	Leerlauf- strom	Innen- widerstand	Dauer- strom	Drehzahl Volt	Gewicht gr.	Propeller	Modell- gewicht gr.
EFLM4010A	Outrunner Power 10	43	35	5	6-10	2-3	2,10A	0,04 Ohm	30A	1100	122	10x5-12x6	910 1360
EFLM4015A	Outrunner Power 15	50	35	5	8-12	2-4	2,00A	0,03 Ohm	34A	950	152	10x6-13x6.5	1020 1590
EFLM4025A	Outrunner Power 25	54	35	5	10-14	3-4	2,40A	0,03 Ohm	32A	870	190	11x8-14x7	1400 2500
EFLM4032A	Outrunner Power 32	50	42	5	10-14	3-4	2,40A	0,02 Ohm	42A	770	200	11x7-14x10	1600 2700
EFLM4046A	Outrunner Power 46	55	50	6	12-16	4-5	3,80A	0,04 Ohm	40A	670	290	12x8-14x10	1800 3200
EFLM4060A	Outrunner Power 60	62	50	6	16-24	5-7	2,70A	0,06 Ohm	40A	400	380	14x8-16x10	2700 4500
EFLM4110A	Outrunner Power 110	54	63	8	24-32	8-9	1,30A	0,10 Ohm	55A	295	490	17x8-19x10	5000 6800
EFLM4160A	Outrunner Power 160	64	63	8	28-32	9-10	1,30A	0,09 Ohm	60A	245	652	18x8-20x10	6800 9000

Änderungen vorbehalten! - Sous réserve de toutes modifications!